

Topaz SR20 Stereo Receiver

November 2014



- True 100 Watts RMS per channel into 8 ohms
- Custom low flux toroidal transformer for audiophile performance
- Impressive connectivity with 3 rear analogue inputs, 3 digital inputs, 1 phono input and 1 front mounted MP3 input
- Dedicated subwoofer output
- Fully switchable twin speaker outputs
- Remote control which also controls matching CD10 CD player
- Built-in MM phono stage for turntable connection
- ¼" front mounted headphone socket
- Detachable IEC mains lead – fully upgradable
- Built-in FM/AM tuner with RDS
- Rigid casework design with a brushed aluminium front panel, wrap-over lid assembly and carefully designed mechanicals for resonance control, all to improve sound quality and aesthetics

Detailed Specifications

| | |
|---------------------------|--|
| Power output | 100 watts (into 8 ohms) |
| DAC | Wolfson WM8728 |
| THD (unweighted) | <0.01% @ 1kHz, 80% of rated power <0.15% 20Hz – 20kHz, 80% of rated power |
| Frequency response (-1dB) | 5Hz – 50kHz |
| S/N ratio (ref 1W) | >82dB (unweighted) |
| Input impedances | 47k ohms |
| Power amp damping factor | >50 |
| Maximum power consumption | 500W |
| Bass/treble controls | Shelving, ultimate boost/cut, +/-10dB@100Hz and 20kHz |
| Subwoofer output | 200Hz 2 nd order L+R, level follows volume setting |
| Digital inputs | PCM 16-24-bit S/P DIF coaxial 32-192kHz TOSlink optical 32-96kHz |
| Tuner | FM/AM (EU and US bands) |
| Dimensions (H x W x D) | 110 x 430 x 340mm (4.3 x 16.9 x 13.4") |
| Weight | 8.1kg (17.8lbs) |



Topaz SR20 Stereo Receiver