

CS-375D CD Receiver System

SILVER | BLACK | BLACK | BLACK



High-class Sound That's Accessible to Everyone

Enjoy full-scale sound on the compact CS-375D system from Onkyo. New switching amp with Optimum Audio Control calibration brings out the best in the supplied 2-Way stereo loudspeakers, each featuring a quality 130 mm woofer and precision 25 mm dome tweeter. This efficient amp generates high driving power for increased sound pressure, projecting music deep into your room and reproducing full-bandwidth signals at high resolution. Enjoy clear, rich vocals, muscular bass, and lively dynamics with music that's cued up fast using the new spin-and-play JOG dial. Whether navigating a USB flash-memory drive filled with music, browsing 40 preset FM/RDS and DAB+ stations, or selecting a CD track, you can find what you need without stress. Stream from smartphone and PC using wake-and-play *Bluetooth*® technology, connect any player via line input, and send TV/PC audio through the speakers via digital input. With excellent sound and smooth operation, the CS-375D is ready to make life better.

CR-375D CD Receiver

PREMIUM SOUND FEATURES

- 20 W x 20 W Stereo Power (6 Ω, 1 kHz, 10% THD, 2 Channels Driven, IEC)
- New Switching Amplification System with Optimum Audio Control Technology for Powerful, Rich, and Detailed Sound
- Full Digital Audio Processing System with High-Performance Filtering
- Direct Mode for Authentic Sound-source Reproduction
- S.Bass Function
- Bass and Treble Tone Controls

EASY CONTROL AND PLAYBACK

- Quick and Intuitive Operation with JOG Dial Selection
- Easy-to-Read Front-Panel Dot-matrix Display
- Wirelessly Stream Audio from Smartphone, Tablet, and PC with *Bluetooth*® Version 4.1 +EDR (A2DP/AVRCP) with Wake On Play, *Bluetooth* Standby, and Auto Connect Functions

- USB Flash-memory Playback via Front USB Input with Easy Navigation via JOG Dial or Remote Controller
- DAB+ Radio Tuner with 10-Station Memory Preset
- FM/RDS Radio Tuner with 30-Station Memory Preset
- Battery-free Memory Backup
- Front-loading CD Player Supports Audio CD, CD-R, CD-RW, and MP3-encoded CD*
- 3 Playback Modes for CD (Normal/Random/Repeat)

* Discs must be properly finalized.

CONNECTION FEATURES

- Main RCA Analog Line Input for External Devices (Rear)
- Optical Digital Input (Rear)
- USB Input (5 V / 0.5 A) for Audio Playback via USB Flash-memory Device (Front)
- FM/DAB+ Antenna Input
- Speaker Posts with Screw Knobs
- 3.5 mm Headphone Jack
- AC Inlet for Power Cord

OTHER FEATURES

- Isolator Feet to Reduce Vibration
- Sleek, Compact, and Uncluttered Styling
- Memory Playback Function
- Program Timer (Daily/Once)
- Sleep Timer (10/20/30/60/90/120/150/180 minutes)
- 3-Stage Display Dimmer (Bright/Dim/Dimmer)
- Speaker Cables and Speaker Cushions
- Simple Remote Controller with Batteries

D-075 2-Way Speakers

- Responsive 130 mm Natural Pulp-fiber Pressed-cone Woofer
- Precision 25 mm Soft-dome Tweeter
- Thick Anti-resonant MDF Baffle with Stylish Matte Finish
- Solid Acoustic-suspension Enclosure
- Removable Cloth Grilles
- Impedance: 6 Ω
- Max. Input Power: 20 W
- Frequency Response: 55 Hz–40 kHz



CS-375D CD Receiver System

Fluent and Immersive Sound with New Switching Amp Featuring Optimum Audio Control Technology

The CS-375D features an efficient switching amplification system that delivers high speaker-driving power, maximizing sound-pressure levels for better energy and punch over an expansive soundstage. Drawing on 70 years of audio engineering experience, Onkyo developed Optimum Audio Control to integrate amplification and speaker characteristics with factory DSP tuning, resulting in perfectly harmonized performance. Expect an exceptionally rich and expressive vocal range, agile dynamics, and clarity of detail true to the source. The CS-375D is ideal for enthusiasts looking for top-shelf sound on a modest budget.



Note: Appearance of final product may differ to that shown.

Cue Music Fast with New JOG Dial

Spin, press, and play... listening to music is that easy. Simply push the JOG dial with a finger to cue up your desired music in moments. No more fiddly and unresponsive buttons—the CS-375D is designed for fast playback control right from the front panel.



Quality 2-Way Speakers

The receiver is paired with quality D-075 2-Way bookshelf loudspeakers. Each includes a 130 mm pressed cone woofer made from stiff yet lightweight natural pulp fiber that's particularly expressive of vocal nuances with plenty of deep, taut bass. Soft-dome tweeters sound clean and unstrained well into the high frequency range, with unwanted resonance absorbed by thick MDF baffles. Enjoy full-scale sound in a smaller footprint from a system design to work in harmony.



Bluetooth® Transforms Mobile Sound Into Room-filling Music

With Bluetooth wireless technology, you can tap and stream virtually any audio playing on your phone, smartphone, tablet, laptop, or PC with minimal loss in quality. Auto Connect function and wake-on-signal detection gets wireless music happening in moments.



Plug-and-Play Audio via USB Input

Plug a flash-memory device into the front USB input and access your digital music anytime using the JOG dial or remote control. With gigabytes of storage more affordable than ever, this USB playback feature can put hundreds of albums at your fingertips.



DAB+ and FM/RDS Tuners

Scan and save 40 FM/RDS and DAB+ radio stations for easy one-touch recall anytime. RDS function displays song information and more. DAB+ tuner brings a big variety of programming to your listening space, from news and talk to music and sports.



Convenient Front-loading CD Player

Smooth front-loading tray lets you place your CDs inside with less chance of scratches. Modes for track, album, and repeat, plus a random playback option, are all useful inclusions. The receiver plays Audio CD, CD-R/RW formats, and your homemade MP3 discs*.

* Discs must be properly finalized.

Analogue and Digital Audio Inputs

Send PC or TV audio through receiver and speakers via rear optical digital input—great for dorm rooms or enhancing a bedroom TV. RCA analog input can connect audio players, phone, or tape deck.

SPECIFICATIONS

CD RECEIVER SECTION

Amplifier Section

Power Output 20 W + 20 W (6 Ω, 1 kHz, 10% THD, 2 Channels Driven, IEC)

THD+N (Total Harmonic Distortion + Noise) 0.05% (1 kHz, 1 W)

Input Sensitivity and Impedance 400 mV/34 kΩ (Line)

Tone Control ±6 dB, 60 Hz (Bass)

±6 dB, 10 kHz (Treble)

Signal-to-Noise Ratio 90 dB (Line, IHF-A)

Speaker Impedance 6 Ω

Tuner Section

Tuning Frequency Range

FM 87.5 MHz–108 MHz

DAB+ 174.928 MHz–239.2 MHz

FM Preset Memory 30 Stations

DAB+ Preset Memory 10 Stations

General

Power Supply AC 220–240 V, 50/60 Hz

Power Consumption 20 W

Bluetooth Standby Power Consumption 0.5 W

Standby Power Consumption 0.5 W

Dimensions (W x H x D) 215 x 117 x 296.5 mm

Weight 2.2 kg

SPEAKER SECTION

Speaker Type 2-Way Acoustic Suspension

Drivers

Woofer 130 mm Cone

Tweeter 25 mm Soft-dome

Frequency Response 55 Hz–40 kHz

Output Sound Pressure Level

82.5 dB/W/m

Max. Input Power 20 W

Nominal Impedance 6 Ω

General

Dimensions (W x H x D) 160 x 250 x 184 mm

Weight 2.6 kg

CARTON

Dimensions (W x H x D) 348 x 375 x 464 mm

Weight 9.1 kg

Supplied Accessories

- AC power cable • Speaker cables (x2) • Quick Start Guide
- Indoor FM/DAB+ antenna • Speaker cushions (x8)
- Remote controller • AAA (R03) batteries for remote (x2)
- Safety brochure • Warranty card



CR-375D (S) Rear View

Due to a policy of continuous product improvement, Onkyo reserves the right to change specifications and appearance without notice. The Bluetooth® word mark and logos are owned by the Bluetooth SIG, Inc. All other trademarks and registered trademarks are the property of their respective holders.



<http://www.onkyo.com/>

Copyright © 2017 Onkyo Corporation. All rights reserved.

NPR No. 17N24 06/17