

Supplemental to New Product Information (SNPI)**TEAC****UD-301-X**

USB DAC



Shrinking high-performance audio into a desktop-friendly package, this is a full-fledged dual monaural DAC (digital to analogue converter)

■ Features at-a-glance

- Compact **DAC (digital to analogue converter)** with USB Audio input
- Supports DSD128 Native and PCM 384kHz/32-bit Hi-Res audio
- Asynchronous Transfer Mode and Up-conversion to 192kHz
- Dual monaural design to eliminate cross-talk between Left and Right channels
- BurrBrown PCM1795 32-bit DAC for each channel
- Toroidal-core power transformer
- XLR analogue balanced output
- Selectable output modes (Fixed, Variable, and Off) allow use as a Pre-amplifier with USB DAC
- Headphone sound can be improved by switching off XLR/RCA outputs
- Full-metal body



Brand	TEAC	
Series	Reference 301 series	
Model	UD-301-X-B	UD-301-X-S
Color	Black	Silver
UPC code	43774033737	43774033744
EAN code	4907034222438	4907034222445
Overall dimensions (W x H x D) NW	215 x 61 x 238 / 8.5" x 2.4 x 9.4" 2.0kg / 4.4 lbs	
Carton dimensions (W x H x D) GW	391 x 150 x 396 / 15.4" x 5.9" x 15.6" 2.8kg / 6.4 lbs	
Quantity per Master Carton	1	

■ Product overview

The UD-301-X is a USB DAC in the Reference 301 range, with a low-profile and small footprint that comfortably fits into the smallest spaces on desktops.

Supports the playback of DSD128 and PCM 192 kHz /32-bit content from PC/Mac and features an improved analogue audio stage delivering excellent sound quality to your existing hi-fi system.

In addition, an innovative CCLC headphone amplifier circuit allows you to use the UD-301-X as a high-grade, standalone headphone amplifier as part of a minimalist desktop system, comprising which a computer, headphones and the UD-301-X.

Supports DSD Hi-Res audio, and dual-monoaural circuit design

● Supports DSD128 Native playback

The UD-301-X is equipped with a USB port supporting DSD Native playback. This directly converts DSD signals into an analogue waveform in ASIO2.1 and DoP formats, without changing the PCM format. In addition, asynchronous transfer mode is also supported for accurate data transfer by referencing the more accurate on-board clock of the AI-301DA-X. Furthermore, a free TEAC HR Audio Player allows users to play back Hi-Res files such as DSD128 and PCM192/32 from Windows/Mac without the need for complicated configuration.



● USB streaming supporting asynchronous transfer mode

As digital audio data travels from a computer to the UD-301-X via a USB cable, timing control for sending/receiving data packets is defined by the UD-301-X's internal clock which is much more accurate than that of most computers. This asynchronous transfer mode theoretically eliminates signal-compromising jitter, and allows digital audio signals to travel in electrically 'cleaner' conditions.

● Up to 192kHz up-conversion

When handling digital audio signals of 96kHz or less, you are able to up-convert them to double or quadruple the original signal sampling frequency. Even when playing back a conventional CD (which is 44.1kHz), a smoother analogue audio signal is obtained by up-converting to a higher sampling frequency. This up-conversion function can be disabled, according to the user's preference.

● Dual monoaural design to eliminate signal interference

In order to process Hi-Res audio data under the best conditions, the UD-301-X employs a dual monoaural circuit design whereby each of the left and right channels comprises its own single monoaural circuit. This circuit design avoids mutual interference between left and right channels and enables improved stereo playback.



● High-performance BurrBrown PCM1795 32-bit DACs

At the heart of its digital audio section, the UD-301-X uses a pair of 32-bit processing DACs (digital to analogue converters), namely BurrBrown PCM1795s,



Supplemental to New Product Information (SNPI)

one for each channel. These high-performance DACs are capable of processing large amounts of data such as DSD128, rendering more accurate playback of Hi-Res audio sources.

- **MUSES8920 Op-amps for high quality analogue audio processing**

On the analogue processing side, key to defining final sound quality, the MUSES8920 Op-amps developed by New Japan Radio Corporation are employed to process the I-V conversion which turns output current from the DACs into voltage signals. A dual-monaural approach is also applied to this stage of processing.



- **CCLC for dual-mono headphone amplifier circuit**

When listening to Hi-Res music via the UD-301-X's dual-monaural headphone amplifier circuit, the CCLC (Coupling Capacitor-Less Circuit) delivers a rich bass sound and quick transient responses. Conventional headphone amplifier circuits cannot avoid reduction of low frequencies and misalignment of phase caused by high-pass filtering within capacitors as they couple output stages.

- **Also works as a standalone headphone amplifier**

In addition to its dual monaural headphone amplifier circuit design, the UD-301-X further strengthens its credentials as a headphone amplifier by offering the ability to disable XLR and RCA outputs on the rear panel. This limits power supply to the headphone amplification process, so maximizing its potential for headphone output. The UD-301-X offers ease of use as a headphone amplifier because the headphone volume is always varied by the master volume control on the front panel, regardless of the output mode (fixed, variable or disabled).

- **Toroidal-core power transformer for plenty of power**

The UD-301-X features an energy-efficient Toroidal-core power transformer to deliver plenty of stable current to every single part of the circuit, including two high-performance DACs (digital to analogue converters) that carry out ultra-high-speed processing. Even when there are sudden dynamic swings, where large amounts of current are required instantly, the UD-301-X's power supply will prove equal to the task.



- **Robust aluminum body, and small footprint**

A 215mm width and 238mm depth creates a footprint that allows you to place the unit in the smallest of spaces, while the full-metal body provides excellent rigidity and minimizes the adverse effects of vibration on final sound quality.

- **XLR Balanced outputs**

The UD-301-X is capable of working as a high-performance DAC with professional audio equipment and high-end audio units, as well as with consumer hi-fi components, thanks to its pair of XLR Balanced output terminals.

- **Pre-amplifier mode to connect with power amplifier**

The output from both XLR Balanced and RCA Unbalanced outputs can be set to, fixed, variable or disabled, depending on your needs. This flexibility, among other things, allows you to connect to power amplifiers for a separates-based system or, indeed, active speakers when the unit is set to variable mode.

■ Key Features

- Supports DSD64 and DSD128 native playback (on USB Input)
- Supports PCM 192kHz/24-bit playback
- Asynchronous Transfer Mode
- Up-conversion to 192kHz (user defeatable)
- Dual 32-bit BurrBrown PCM1795 DACs
- Dual monaural circuit design
- Dual MUSES8920 Op-amps
- Dual monaural CCLC Headphone amplifier circuit
- Toroidal-core power transformer
- Full-metal body
- USB Audio input
- Coaxial digital audio output
- Optical digital audio output
- XLR analogue balance output (Output level: Fixed, Variable, Disabled)
- RCA analogue unbalanced output (Output level: Fixed, Variable, Disabled)
- Headphone output (1/4" Stereo phone jack)
- Detachable power cable
- Auto-power saving
- RoHS compliant

■ Specifications**Supported formats**

USB Audio input

DSD	DSD128 (5.6MHz), DSD64 (2.8MHz)
PCM	16, 24, 32-bit, 32k, 44.1k, 48k, 88.2k, 96k, 176.4k, 192kHz

Coaxial digital input

PCM	16, 24-bit, 32k, 44.1k, 48k, 88.2k, 96k, 176.4k, 192kHz
-----	---

Optical digital input

PCM	16, 24-bit, 32k, 44.1k, 48k, 88.2k, 96kHz
-----	---

DAC section

D/A Converter	BurrBrown PCM1795 x 2
Up-conversion	Max 192kHz (On/Off selectable)

Audio Inputs/Outputs

USB Audio input

Connector	USB B-type x 1
USB version	USB2.0
Transfer mode	Asynchronous transfer mode
Recommended software	TEAC HR Audio Player (Mac, Windows)

Supplemental to New Product Information (SNPI)

Coaxial digital audio input

Connector	RCA Pin x 1
Impedance	75 ohms
Input level	0.5Vp-p

Optical digital audio input

Connector	TOS-link x 1
Input level	-24.0 to -14.5dBm peak

Analog balanced output

Connector	XLR 3-32 x 1 pair
Impedance	200 ohms
Max output level	+14dBu (1kHz, Full-scale, 10k ohms loaded, 0dB setting)

Analog unbalanced output

Connector	RCA Pin x 1 pair
Impedance	100 ohms
Max output level	2.0Vrms (1kHz, Full-scale, 10k ohms loaded)

Headphone output

Connector	1/4" (6.3mm) Stereo headphone jack x 1
Supported impedance	16 to 600 ohms
Max output power	100mW + 100mW (32 ohms loaded, THD 0.1%)

Audio performance

Frequency response	5Hz to 55kHz (-3dB, Sampling frequency: 192kHz)
Signal-to-Noise ratio	105dB
Total harmonic distortion	0.0015% (1kHz, Sampling frequency: 192kHz)

Supported OS

Windows

Windows 10 (April 2018 Update) , Windows 10 (November Update) , Windows 8.1 , Windows 8 , Windows 7 , Windows Vista , Windows XP (32bit ver.)

Mac

macOS High Sierra (10.13) , macOS Sierra (10.12) , OS X El Capitan (10.11) , OS X Yosemite (10.10) , OS X Mavericks (10.9) , OS X Mountain Lion (10.8) , OS X Lion (10.7) , Mac OS X Snow Leopard (10.6)

Please check the latest information on the web page: <https://teac.jp/int/product/ud-301/spec>

General

Operating power	AC 120V, 60Hz (US/Canada) AC 230V, 50Hz (UK/Europe)
Power consumption	10W
Overall dimensions (W x H x D)	8.5" x 2.4" x 9.4" / 215 x 61 x 238mm
Net weight	4.4 lbs. / 2.0kg

Supplemental to New Product Information (SNPI)

TEAC

Included items

AC power cable x1

Owner's Manual (including Warranty)

■ Rear Panel

