

marantz®



NR1608 ULTRA-SLIM 7.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING



A thrilling high-quality AV receiver occupying minimal space: that's the NR1608. High current discrete power amplifiers on all 7 channels deliver astonishing power and clarity, plus immersive 3D surround sound thanks to both Dolby Atmos and DTS:X decoders, yet at just a little more than 10 cm tall it's slim enough to slip into any TV cabinet. It's fully compatible with the latest HDMI and HDCP 2.2 specifications, including 4K video with High Dynamic Range (HDR) and Dolby Vision compatibility. Bluetooth and AirPlay can stream music directly from portable devices, while HEOS wireless multi-room music integration allows the NR1608 to become part of a complete home-wide music system. Explore and play your own music library, online streaming music services and thousands of Internet radio stations, using the free HEOS app.

Highlights

- Slim Design 7.2 channel AV Receiver with 90W per channel
- Built-in WiFi with 2.4GHz/5GHz dual band support; built-in Bluetooth
- 4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR and BT.2020, plus Dolby Vision compatibility and Hybrid Log Gamma (HLG; via future firmware update)
- 8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support
- Analogue to HDMI conversion and SD/HD to 4K Upscaling for legacy video sources
- Dolby Atmos (up to 5.1.2) and DTS:X
- AirPlay, Bluetooth, Internet Radio, Spotify Connect, Network Audio Streaming
- DSD (2.8/5.6MHz), FLAC, ALAC and WAV support
- Audyssey MultEQ, Dynamic Volume and Dynamic EQ
- Colour-coded speaker terminals, Setup Assistant, Marantz AVR Remote App
- Intelligent ECO mode with off/on/auto setting

Your Benefits

- Enough power to fill medium size rooms from a small cabinet with renowned Marantz sound
- Improved network stability especially in WiFi-crowded homes
- Latest HDMI standard for future-proof compatibility
- Plenty of inputs for your Blu-ray Player, game console and more
- Full HD and even Ultra HD video quality from existing DVDs or analogue sources
- Immersive 3D sound with effects from overhead
- Access to almost unlimited online music sources
- High Resolution audio streaming, even gapless
- Delivering perfect equalization for your individual room
- Hassle-free installation, setup and operation
- Energy-conscious without compromising on performance



because music matters

NR1608

ULTRA-SLIM 7.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING



Design and specifications are subject to change by Marantz without notice.

FEATURES	NR1608
MULTICHANNEL SURROUND	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAX2	•
Audyssey	MultEQ
Audyssey Dynamic EQ / Dynamic Volume	• / •
Audyssey MultEQ Editor App support	•
NETWORK / SOURCES	
Network Audio Streaming	•
HEOS Multiroom integrated	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	•
Internet Radio (TuneIn)	•
Spotify Connect, Deezer, TIDAL, Napster, Soundcloud *	• / • / • / • / • / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna / dual band)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio	•
FM / AM Tuner	• / •
Bluetooth	•
HDMI	
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •
Dolby Vision compatible / Hybrid Log Gamma (HLG)	• / • (via Firmware Update)
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Videoprocessing and -scaling	1080p, 4K 30/25/24Hz

* This feature is not available in all countries.

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3 / 1
Component In / Out	2 / 1
HDMI In / Out	7+1 / 1
AUDIO	
Analogue In / Out	3 / 0
Digital Optical In	1
Digital Coaxial In	1
Multichannel Pre Out	• (2.2)
Zone audio preout	•
Subwoofer Out	2
SPECIFICATIONS	
Number of poweramps	7
Power Output per channel	
6 ohm, 1 kHz, 1%, 1ch Drive	90 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	70 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	50 W
Audio Signal to Noise Ratio	98 dB
GENERAL	
Available colours: Black / Silver-Gold	• / •
System Remote Control	RC034SR
Power Consumption in W	250
Power Consumption No-Sound (ECO ...on/off) in W	30 / 40
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in mm	440 x 376 x 105
Weight in kg	8.3
EAN	
EU	
NR1608/N1B	4951035060490
NR1608/N1SG	4951035060506
UK	
NR1608/T1B	4951035060704
NR1608/T1SG	4951035060711

D&M Europe B.V.
A Division of Sound United
Beemdstraat 11
5653 MA Eindhoven
The Netherlands

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

* All specs can be subject to change.