

## 7.2-ch Class D Network AV Receiver

# SC-LX501(B)/(S)

BLACK SILVER







The SC-LX501 featuring 7.2-ch Class D amplifier is fully-equipped for the latest multi-dimensional surround sound formats, DTS:X<sup>™</sup> and Dolby Atmos<sup>®</sup>, featuring the Reflex Optimizer for Dolby enabled speakers. With Ultra HD (4K/60p/4:4:4) upscaling/passthrough and HDR/BT.2020 standards ready, images are ever more impressive. In addition to internet radio and various network streaming services, with Google Cast<sup>™</sup> built-in you can use your mobile device to cast your favourite music to your receiver. The multizone feature supports powered ZONE 2 output.

## **AMPLIFICATION**

- > Channels: 7
- > Amplification Type: Class D (Direct Energy HD)
- > 560 W Multi-ch Simultaneous Drive (8 ohms, 1 kHz, THD 1.0 %)
- > 270 W/ch (4 ohms, 1 kHz, 1ch Driven IEC)
- > 160 W/ch (8 ohms, 1 kHz, 1ch Driven IEC)

## **CONSTRUCTION DESIGN**

- > Fan-less Cooler Design
- > Anti-Standing Wave Insulator

## **AUDIO FEATURES**

- > Dolby Atmos®/Dolby Surround
- > DTS:X\*1/DTS Neural:X\*1
- > Reflex Optimizer
- > Dolby® TrueHD/Dolby Digital Plus
- DTS-HD Master Audio/DTS-HD High Resolution Audio/DTS 96/24/DTS-ES/DTS-HD Express
- DSD Direct Playback via Network/USB (11.2, 5.6, 2.8 MHz/2ch)
- > DSD Disc (SACD) Playback via HDMI (2.8 MHz/5.1ch, 2ch)
- > Digital Core Engine with Cirrus Logic (Quad Core) x1
- > 384 kHz/32-bit DAC (AK4458)
- > HDMI Audio Return Channel (ARC)
- > MCACC Auto Room Tuning
  - Phase Control
  - Subwoofer EQ (4 Band)
- > Advanced Sound Retriever (2ch)
- > Advanced Surround Modes
  - Classical, Unplugged, Entertainment Show, Drama, Advanced Game, Action, Rock/Pop, Sports, Extended Stereo, Extended Mono, Front Stage Surround, Auto Surround

#### VIDEO FEATURES

- Ultra HD Pass-through with HDCP 2.2 (4K/60p/4:4:4/24-bit, 4K/24p/4:4:4/36-bit, 4K/60p/4:2:0/36-bit)
- > HDR and BT.2020 Support
- ) Ultra HD Upscaling (1080p  $\rightarrow$  4K)
- > 3D Ready (Blu-ray Disc™, Broadcast, and Games)
- > Deep Colour (36-bit), "x.v.Colour"

## HOME NETWORK FEATURES

- > FireConnect™\*¹ for Multi-room Audio
- > Google Cast\*1\*2
- > Apple AirPlay Certified
- > Spotify® Digital Music-Streaming Service Ready\*3
- > Internet Radio with TuneIn
- > TIDAL Music Streaming Service Ready\*1
- > Deezer\*1\*4
- > Hi-Res Audio File Playback via USB/Network
  - Up to 192 kHz/24-bit ALAC, AIFF, FLAC, WAV
  - 11.2/5.6/2.8 MHz DSD Playback
  - Dolby® TrueHD Playback (USB only)

## **CONVENIENCE FEATURES**

- > Built-in Wi-Fi® (Dual Band 5 GHz/2.4 GHz)
- Built-in Bluetooth® Wireless Technology (Version: 4.1, Profile: A2DP/ AVRCP, Codec: SBC/AAC)
- iControlAV5 Remote Control App Ready (iOS/Android)\*5
- > New GUI with System/Network Setup Menu
- > Auto Power Off in HDMI Standby Through
- > AM/FM Tuner 40 Presets
- > Sleep Time
- > User-Friendly Simple Remote Control

## FRONT TERMINALS

- > HDMI 1 In
- > USB 1 In for USB Drive
- > MCACC Setup MIC In
- > Phones 1 Out

## **REAR TERMINALS**

- > HDMI 6 In (4 Assignable)
- > HDMI 2 Out (1 for MAIN, 1 for SUB)
- > Ethernet 1 In
- > AV (Component) 1 In (Assignable)

- > AV (Composite) 2 In (Assignable)
- > Audio 1 In (Assignable)
- > Phono (MM) 1 In
- > Digital Coaxial 1 In (Assignable)
- Digital Optical 2 In (Assignable)
- > Subwoofer 2 Pre Out
- > Zone 2 Pre/Line Out
- > Speaker 9 ch Out (FRONT, CENTER, SURROUND, SURROUND BACK/ZONE 2/ Bi-AMP, HEIGHT/SP B)
- > IR 1 In/1 Out
- > 12 V Trigger 2 Out/RS-232C

> FM/AM Antenna

## **SPECIFICATIONS**

- > Power Requirements: AC 220-230 V, 50/60 Hz
- > Power Consumption/Standby: 250 W/0.2 W
- Dimensions (W x H x D): 435 x 185 x 395 mm
- > Weight: 12 kg

<sup>\*1</sup> Available with future firmware update \*2 Compatible apps required \*3 For service availability in your country, check www.spotify.com

<sup>\*</sup>⁴ For service availability in your country, check www.deezer.com \*⁵ Available for free download from the App Store/the Google Play™



#### SC-LX501(B)/MGP

## Multi-Dimensional Excitement with Dolby Atmos®

The SC-LX501 is compatible with 5.2.2ch configuration of the latest cinema sound platform, Dolby Atmos®. You can reproduce object-oriented sound in smooth, curving movements, or the realistic three-dimensional movement overhead by the top speakers.



Dolby Atmos 5.2.2ch Speaker System




## DTS:X™ Ready

DTS:X is the next-generation audio codec from DTS that leverages object-based audio to enable new immersive and interactive audio experiences. Since DTS:X can automatically adapt the audio to the existing channels and speaker system, no specific speaker layout is required. Experience an immersive soundscape with incredibly rich and life-like audio.

\* DTS:X will be available with future firmware update

## **Google Cast**

The SC-LX501 has Google Cast, the same technology behind Chromecast built-in, so you can use vour mobile device to cast your favorite music, radio, or podcasts to your speaker. You



\* Google Cast will be available with future firmware update.

## Ultra HD (4K/60p/4:4:4/24-bit) Upscaling/Pass-Through with HDCP 2.2

The feature lets you take advantage of the highestquality video source for viewing on a 4K TV. With support for HDCP 2.2, you can enjoy premium content such as 4K videos with digital copy protection on a compatible display. What's more, the SC-LX501 is ready for the HDR (High Dynamic Range) and BT.2020 next generation video standards.



Google Cast

\* Supports up to 4K/60p/4:4:4/24-bit with HDCP 2.2 on HDMI IN (1/2/3) and HDMI OUT (MAIN/SUB).

HDR Dynamic Range Expansion Image





For illustration purpose only

## MCACC Auto Room Tuning

Create the optimum acoustic environment with Pioneer's MCACC (Multi-Channel Acoustic Calibration System), developed with the expertise of professional recording studios. With the custom microphone, the system automatically compensates for differences in speaker size, level and distance, and equalises response.


## **Synchronised Sound with Phase Control**

As an innovative solution for the phase lag between the subwoofer and the main channel speakers caused by the network filter, Phase Control compensates the delayed bass to improve sound synchronisation.



## **Reflex Optimizer**

High directivity sound reflects off the ceiling, while low directivity sound directly reaches the ears. This difference causes a phase shift, making the sound feel uncomfortable. To solve this, the new technology optimizes the performance of your up-firing elevation speakers for your listening environment, by aligning the phase of direct and indirect sound, matching the basic tone, and optimizing the upward-oriented



frequencies. The result is overall seamless sound with Dolby enabled speakers, allowing the ideal reproduction of three-dimensional surround sound.

## Multi-room Audio Offers a Variety of Ways to Enjoy

The SC-LX501 will support FireConnect™ Powered by Blackfire\* with future firmware update. FireConnect is a stable wireless protocol that mirrors any audio source connected to the receiver—from vinvl to streaming audio—on optional FireConnect compatible speakers\*\* in other rooms.



- \* Multi-room Audio is realised by FireConnect technology. FireConnect is a technology of Blackfire Research Corp, USA. We do not guarantee that the AV Receiver will support all devices incorporating FireConnect.
- \*\* FireConnect compatible speakers will be released going forward

































