


R-41PM

Klipsch
REFERENCE



TURNTABLE READY



BLUETOOTH®
WIRELESS TECHNOLOGY



PC READY



NO RECEIVER NEEDED



TV READY



SIMPLE SETUP



SPECIFICATIONS

SYSTEM DESCRIPTION	Powered Monitor (pair)
FREQUENCY RESPONSE	76Hz - 21kHz
DYNAMIC BASS EXTENSION	66Hz @ 35% Volume
MAX OUTPUT	105.5dB
TOTAL SYSTEM POWER	70W Total System Power (140W Peak) 35W per channel cont. @ <1% THD
HIGH FREQUENCY DRIVER	1" (2.5cm) Aluminum diaphragm compression driver mated to 90° x 90° square Tractrix® horn
LOW FREQUENCY DRIVER	4" (10.2cm) copper spun magnetically shielded IMG woofer
CROSSOVER FREQUENCY	1730 Hz (Passive)
ENCLOSURE MATERIAL	MDF
ENCLOSURE TYPE	Bass-reflex via rear-firing port
INPUTS	• Bluetooth® wireless technology • Phono/Line analog (with switch and ground screw terminal) • 3.5mm analog mini jack • USB digital • Optical digital
OUTPUTS	Single RCA line level output for connection to subwoofer
HEIGHT, WIDTH, DEPTH	11.3" (28.7 cm), 5.75" (14.6 cm), 8.51" (21.6 cm)
WEIGHT	8.1 lbs (3.7 kg)
FINISH	Black
VOLTAGE	100V-240V 50/60Hz internal power supply with region specific power cords
INCLUDED ACCESSORIES	• Remote control (with 2 x AAA batteries) • 4M speaker wire with soldered tips • 2M power cord (region specific) • 2M USB Type A to Type B cable • Rubber feet
BUILT FROM	2018

SOUND THAT PACKS A PUNCH

A truly powerful, small form-factor music monster packed with Klipsch acoustics with integrated power and Bluetooth® wireless technology.

DESIGNED FOR SIMPLE SET UP WITH YOUR TURNTABLE, TV, COMPUTER OR WIRELESS DEVICE

With an integrated phono pre-amp, Bluetooth® wireless technology, digital optical, analog RCA and USB inputs, your R-41PM is the best performing, most versatile monitor on the planet.

DYNAMIC BASS EQ

As the human ear perceives frequencies differently with variations in output, the R-41PM will dynamically match the ear's ability to hear lower frequencies. Typically, only available with audio/video receivers, dynamic volume is a first for Klipsch powered monitors. What you get is powerful bass whether the listening volume is low, cranked up or somewhere in between.

HIGH EFFICIENCY AMPLIFICATION

Forget the expense, clutter and hassle of an external A/V receiver. The R-41PM monitors incorporate individual ultra-low noise amplifiers custom designed to maximize system performance and eliminate the need for external amplification.

FULL FEATURED IR REMOTE

Allows easy access to system features like dedicated source selection, track controls, and play/pause.

SYSTEM EXPANDABILITY

Add a subwoofer to enhance for even more bass.

Klipsch
KEEPERS OF THE SOUND

3502 WOODVIEW TRACE INDIANAPOLIS, IN 46268 | KLIPSCH.COM

All specifications are subject to change without notice. ©2018 Klipsch Group, Inc. Klipsch, Keepers of the Sound and Tractrix are registered trademarks of Klipsch Group, Inc. a wholly-owned subsidiary of Vox International Corporation. The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Klipsch Group, Inc. is under license.