

# marantz®



## SR5014 7.2CH 4K ULTRA HD AV RECEIVER WITH HEOS BUILT-IN

Refine your home cinema with the Marantz SR5014 7.2 channel 4K UHD AV receiver. Enjoy the most musical sound for any source, from vinyl to digital streaming. Envelop yourself with immersive surround formatting from Dolby Atmos and DTS:X. Enjoy seamless voice control from the leading voice agents, multi-room connectivity and advanced HDMI technology.

### Highlights

### Your Benefits

7.2 channel AV Receiver with 180W per channel	Enough power to fill bigger rooms with renowned Marantz sound
Built-in WiFi with 2.4GHz/5GHz dual band support; built-in Bluetooth	Improved network stability especially in WiFi-crowded homes
4K/60 Hz full-rate pass-through, 4:4:4 colour resolution, HDR and BT.2020, plus Dolby Vision compatibility and Hybrid Log Gamma (HLG)	Full compatibility with the latest video standards for best picture quality
8 HDMI inputs (incl. 1 front) with full HDCP 2.3 support; 2 HDMI outputs, with 1 HDMI output supporting eARC	Ready for all your source players and easy connection to a TV and projector
Analogue to HDMI conversion and SD/HD to 4K Upscaling	Full HD and even Ultra HD video quality from all sources
Audyssey MultEQ XT, Dynamic Volume and Dynamic EQ	Delivering perfect equalization for your individual room
Dolby Atmos (up to 5.1.2), DTS:X and DTS Virtual:X processing	Immersive 3D sound with effects from overhead
Audiophile AKM AK4458 32-bit D/A converters; HDAM; Current Feedback	For the most accurate and detailed audio reproduction
AirPlay 2, Bluetooth, Internet Radio, Spotify Free and Premium, Network Audio Streaming	Access to almost unlimited online music sources
Integrated high-quality Phono input	Connect your turntable and listen to your beloved Vinyls
HEOS Built-in	Wireless Multi-room audio, voice control and digital music streaming
Extended multi-room capabilities	Enjoy native surround in main room while distributing same source as 2ch downmix in second zone
DSD (2.8/5.6MHz), FLAC, ALAC and WAV support	High Resolution audio streaming, even gapless
Colour-coded speaker terminals, Setup Assistant, Marantz AVR Remote App	Hassle-free installation, setup and operation
Intelligent ECO mode with off/on/auto setting	Energy-conscious without compromising on performance



# because music matters

## SR5014

### 7.2CH 4K ULTRA HD AV RECEIVER WITH HEOS BUILT-IN



Design and specifications are subject to change by Marantz without notice.

FEATURES	SR5014
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
Dolby Atmos Height Virtualization / DTS Virtual:X	• / •
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAx2	•
Audyssey	MultEQ XT
Audyssey Dynamic EQ / Dynamic Volume	• / •
Audyssey MultEQ Editor App support	•
<b>NETWORK / SOURCES</b>	
Network Audio Streaming	•
HEOS Multiroom integrated	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay2	•
Internet Radio (Tuneln)	•
Spotify Connect, Deezer, TIDAL, Napster, Soundcloud *	• / • / • / • / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna / dual band)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio	•
FM / AM Tuner	• / •
Bluetooth	•
Bluetooth Headphone transmission	•
<b>HDMI</b>	
4K 60Hz 4:4:4 resolution / HDCP 2.3	• / •
Dolby Vision compatible / Hybrid Log Gamma (HLG)	• / •
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Video processing and -scaling	1080p, 4K 30/25/24Hz

\* This feature is not available in all countries.

D&M Europe B.V.  
A Division of Sound United  
Beemdstraat 11  
5653 MA Eindhoven  
The Netherlands

<b>INPUTS/OUTPUTS</b>			
<b>VIDEO</b>			
Composite In / Out			2+1 / 1
Component In / Out			2 / 1
HDMI In / Out			7+1 / 2
<b>AUDIO</b>			
Analogue In / Out			4+1 / 0
Digital Optical In			2
Digital Coaxial In			2
Multichannel Pre Out			• (7.2ch)
Zone audio preout			•
Subwoofer Out			2
7.1 Multichannel input			•
<b>SPECIFICATIONS</b>			
Number of poweramps			7
Power Output per channel			
6 ohm, 1 kHz, 1%, 1ch Drive			180 W
6 ohm, 1 kHz, 0.7%, 2ch Drive			140 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive			100 W
Audio Signal to Noise Ratio			100 dB
<b>GENERAL</b>			
Available colours: Black / Silvergold			• / •
System Remote Control			RC035SR
Power Consumption in W			650
Power Consumption No-Sound (ECO ...on/off) in W			45 / 75
Standby Consumption in W			0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in mm			440 x 348 x 161
Dimensions packed (W x D x H) in mm			519 x 428 x 242
Weight in kg			10.1
Weight packed in kg			12.3
<b>EAN</b>			
<b>EU</b>	SR5014/N1B	4951035069851	Black
	SR5014/N1SG	4951035069837	Silvergold
<b>UK</b>	SR5014/T1B	4951052070199	Black
	SR5014/T1SG	4951053070204	Silvergold

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/third-party-licenses](http://www.spotify.com/connect/third-party-licenses). Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

\* All specs can be subject to change.