

Network Stereo Receiver

SX-S30DAB(B/S)





Enjoy various audio entertainment including Hi-Res Audio files, music streaming services, internet radio, DAB/DAB+, CDs, and vinyl records. Bluetooth* Wireless Technology, Chromecast built-in, AirPlay, and built-in Wi-Fi* let you wirelessly stream songs. If you have Chromecast built-in or Apple TV, you can listen to songs by plugging them to the HDMI terminal. Just connect the speaker of your choice, and play and listen the way you like.

AMPLIFICATION & DESIGN

- > Channels: 2
- Amplification Type: Class D
- 85 W/ch (4 ohms, 1 kHz, THD 1.0 %, 1ch Driven)

NETWORK FEATURES

- FireConnect[™] for Multi-room Audio
- Chromecast built-in*2
- Apple AirPlay Certified
- Spotify[®], TIDAL, and Deezer Music Streaming Services Ready^{*3}

.....

Internet Radio (TuneIn)

AUDIO FEATURES

- > MCACC Auto Room Tuning
 - Phase Control
 - Subwoofer EQ (4 Band)
- DSD Playback via Network/USB (5.6 MHz/2.8 MHz)
- DSD Disc (SACD) Playback via HDMI (2.8 MHz)

.....

- Digital Core Engine with Cirrus Logic (Quad Core) x1
- Advanced Sound Retriever

CONNECTIVITY & CONTROL

- > HDMI 4 In/1 Out
- Plug and Play External HDD and USB Memory via Front USB*4

.....

- Works with Pioneer Remote App (iOS/Android)*5 >
- Built-in Wi-Fi (Dual Band 5 GHz/2.4 GHz) > Built-in Bluetooth^{*} Wireless Technology (Version: 4.1, Profile: A2DP/AVRCP, Codec: SBC/AAC)

CONVENIENCE

- DAB/DAB+ Tuner
- FM Tuner with 40 Station Presets
- Dimmer >
- Firmware Update (USB/Network)

FRONT TERMINALS

- > USB 1 In for USB Drive
- Phones 1 Out

REAR TERMINALS

- > HDMI 4 In
- HDMI 1 Out (ARC)
- > Ethernet 1 In

> Audio 2 In (Assignable)

- > Phono (MM) 1 In
- MCACC Setup MIC In
- Digital Coaxial 1 In (Assignable)
- Digital Optical 1 In (Assignable)
- Subwoofer 1 Pre Out
- Speaker Out (L/R)
- FM/DAB Tuner Antenna

SPECIFICATIONS

.....

- Power Requirement: AC 100-240 V, 50/60 Hz
- › Power Consumption: 55 W
- Power Consumption During Standby: 0.38 W (2 W Network Standby On)
- Dimensions (W x H x D): 435 x 78 x 330 mm
- Weight: 4.0 kg

*² Compatible apps required *³ Service availability depends on region *⁴ Supports HDD/USB memory formatted with FAT32. Not guaranteed to work with all HDD/USB memory devices. *⁵ Available for free download from the App Store/the Google Play^{**}



SX-S30DAB(S)/MUP

Streaming Services & Internet Radio

Enjoy listening to whatever music you like with streaming services such as Spotify, TIDAL, and Deezer. The unit is also preset with TuneIn for enjoying internet radio. With over 100,000 radio stations, you can listen to free broadcasts of music, sports, news and talk shows from around the world. * Service availability depends on region



Connect with Chromecast built-in, AirPlay, and Wi-Fi

With Chromecats built-in, you can use your mobile device to cast your favorite music, radio, or podcasts to your speaker. You can control the audio from anywhere in the house using Cast-enabled apps. You can also stream songs from your music library with AirPlay, or enjoy network features via dual band (5 GHz/2.4 GHz) Wi-Fi.





Versatile Connectivity

The SX-S30DAB is equipped with the phono MM input for a vinyl record player, as well as optical and coaxial digital inputs for connecting other audio sources. The HDMI terminal lets you plug your Chromecast or Apple TV and enjoy streaming songs.



DAB/DAB+ Radio

Enjoy radio broadcasts in crystal clear sound, free of interference. The built-in DAB/DAB+ tuner lets you listen to various programmes by automatically tuning in to available stations.

Hi-Res Audio File Playback via USB/Network

You can play up to 5.6 MHz DSD (Direct Stream Digital) files, and up to 192 kHz/24-bit WAV, FLAC, AIFF, and Apple Lossless files from HirRes a USB device or via wired or wireless network. AUDIC

MCACC Auto Room Tuning

Create the optimum acoustic environment with Pioneer's MCACC, developed with the expertise of professional recording studios. With the custom microphone, the system automatically compensates for differences in speaker size, level and distance, and equalises response. As an innovative solution for the phase lag between the subwoofer and the main channel speakers caused by the network filter, Phase Control compensates the delayed bass to improve sound synchronisation.



Multi-room Audio Offers a Variety of Ways to Enjoy Music

The SX-S30DAB will support FireConnect™ Powered by Blackfire* with future firmware update. FireConnect is a stable wireless protocol that mirrors any audio source connected to the receiver-from vinyl to streaming -on optional FireConnect compatible speakers** in other rooms. audio-



* Multi-room Audio is realized by FireConnect technology. FireConnect is a technology of Blackfire Research Corp, USA. We do not guarantee that the AV Receiver will support all devices incorporating FireConnect.

** FireConnect compatible speakers will be released going forward.

Intuitive Control with New Pioneer Remote App (iOS/Android)

Enjoy smooth control with album artwork using your beloved device. With the free Pioneer Remote app, you can use your iPad/ iPhone/iPod touch or Android smartphone for operating the network audio player, or play back tunes stored on your device. You can also select internet radio stations, and play songs from your media server.



* Receiver needs to be connected to a home LAN network in a wireless LAN environment.



+PIONEER,MCACC,PhaseControl,AdvancedSoundRetriever,andthelogosareregisteredtrademarksofPioneerCorporation,andareusedunderlicense.+ThetermsHDMlandHDMIHigh-DefinitionMultimediaInterface, *PIONECP,/MCLCy/PraseControl,AdvancedSounder(rever,and theirogosarereg)stered trademarkson honeer Corporation, and used underschilder and the PIONEC, and t

> © 2016 Onkyo & Pioneer Corporation. All rights reserved. Note: Specifications and design subject to change without notice.