

STEREO INTEGRATED AMPLIFIER





If you are considering taking your first step into a true hi-fi system or are seeking a small, high quality audio system for another living space, you can't do better than the A10 integrated amplifier. The A10 is all about maximum performance for the price. Its design strips away added features that increase the overall cost and can detract from your musical enjoyment. Simple to operate and a pleasure to listen to, the A10 has connectivity for all your listening sources including an analogue media input (3.5mm mini-jack) for iOS devices or other media players, a CD input, a MM phono input in case your taste runs to classic LPs, a Tuner input to listen to your favourite radio stations and two Aux inputs for other analogue source devices.

Rotel integrated amplifiers bring your sources to life with amazing fidelity. See more at





STEREO INTEGRATED AMPLIFIER

A10



SPECIFICATIONS

Continuous Power Output	40 watts/ch	Preamp Output / Impedance	1 V / 470 Ohms
(20 - 20kHz, < 0.03%, 8 ohms)		Tone Controls - Bass / Treble	± 6 dB at 100Hz / 10kHz
Total Harmonic Distortion (20 Hz - 20 kHz at rated power)	< 0.03%	Signal to Noise Ratio ("A" weighting)	
Intermodulation Distortion (60 Hz : 7kHz, 4:1)	< 0.03%	Phono Input	80 dB
Frequency Response		Line Level Inputs	100 dB
Phono Input	20Hz-15kHz, ±0.3 dB	General	
Line Level Inputs	10Hz - 40kHz, ±1 dB	Power Requirements	
Damping Factor	180	Europe	230V, 50Hz
(20 - 20,000 Hz, 8 ohms)		USA	120V, 60Hz
Input Sensitivity / Impedance		Power Consumption	220 watts
Phono Input	2.5 mV / 47 k Ohms	Finishes	Silver and Black
Line Level Inputs	150 mV / 24 k Ohms	Dimensions (W x H x D)	430 x 73 x 347mm
Input Overload			17" x 2 7/8" x 13 5/8"
Phono Input	180 mV	Front Panel Height	60mm, 2 3/8"
Line Level Inputs	5 V	Weight (net)	5.9kg, 13 lb

Rotel integrated amplifiers bring your sources to life with amazing fidelity. See more at

rotel.com

